

# DESIGN AND IMPLEMENTATION OF GATED S-R LATCH IN ESIM

Mihir Rana

Department of Electronics and Communication Engineering

Institute of Technology Nirma University

Ahmedabad, India

mihirrana620@gmail.com

**Abstract**—In This Paper I am going to Design S-R Latch using Verilog. Design and Implementation will be done in esim and ngspice software. The SR Latch is a bistable 1-bit memory device with two inputs, SET and RESET. The RESET input 'R' resets the device or causes the output 0 to be produced. The SET input 'S' configures the device or generates output 1, while the RESET input 'S' configures the device or generates output 0. S and R are the labels for the SET and RESET inputs, respectively. The main objective was to design a mixed signal circuit for that I have attached ADC in front of S-R Latch and DAC in behind of S-R Latch to get input and output in analog form.

## I. REFERENCE CIRCUIT DETAILS

- Case 1 :  $S = 0$ ,  $R = 0$ , and  $CLK = 1$   
The inputs of both NOR gates are Logic '0' in the first case. They have no effect on the output because neither of them dominates the inputs. As a result, the outputs retain their previous states, i.e., the outputs do not change. This is referred to as a Hold Condition or a No Change Condition.
- Case 2 :  $S = 0$ ,  $R = 1$ , and  $CLK = 1$   
The 'R' input is 1 in this case, indicating that the NOR Gate A output will be 0. (i.e., Q will be 0). (LOW). Both of NOR Gate B's inputs become 0 as a result, and the NOR Gate B's output is 1. (HIGH). Because a '1' at input R causes the output to switch to one of its stable states and then resets it to '0,' it is known as the RESET input.
- Case 3 :  $S = 0$ ,  $R = 1$ , and  $CLK = 1$   
In this case, the 'S' input is 1, indicating that the NOR Gate B output will be 0. As a result, both NOR Gate A's inputs become 0 and the NOR Gate A's output, and thus the value of Q, becomes 1. (HIGH). The S input is known as the SET input because '1' at input S causes the output to switch to one of its stable states and sets it to '1'.
- Case 4 :  $S = 1$ ,  $R = 1$ , and  $CLK = 1$   
This input condition is forbidden because it causes both NOR Gates' outputs to be zero, which is incompatible with complementary outputs. Even if this input condition is met, a 'race condition' between the NOR Gates occurs if the next inputs are  $R = 0$  and  $S = 0$  (hold condition),

resulting in an unstable or unpredictable output state.

- Case 5 :  $CLK = 0$

Regardless of the states of S or R, the outputs of the two AND gates are forced to 0 when  $CLK = 0$ . As a result, the circuit acts as if S and R are both 0, latching the Q and not-Q outputs in their previous states.

## II. TRUTH TABLE

CLK	S	R	Q	$\sim Q$
0	0	0	Latch	Latch
0	0	1	Latch	Latch
0	1	0	Latch	Latch
0	1	1	Latch	Latch
1	0	0	Latch	Latch
1	0	1	0	1
1	1	0	1	0
1	1	1	0	0




Fig. 1. Reference Circuit




Fig. 2. Reference Waveform




Fig. 3. Mixed Signal Circuit Design

## REFERENCES

- [1] SR Flip Flop - Javatpoint. [www.javatpoint.com](http://www.javatpoint.com). (n.d.). Retrieved February 27, 2022, from <https://www.javatpoint.com/sr-flip-flop-in-digital-electronics>
- [2] <https://www.allaboutcircuits.com/textbook/digital/chpt-10/s-r-latch/>